

Universal quantum computation using only projective measurement, quantum memory, and preparation of the $|0\rangle$ state

Michael A. Nielsen*

Centre for Quantum Computer Technology, University of Queensland, Queensland 4072, Australia.
(February 1, 2008)

What resources are universal for quantum computation? In the standard model, a quantum computer consists of a sequence of unitary gates acting coherently on the qubits making up the computer. This paper shows that a very different model involving only projective measurements, quantum memory, and the ability to prepare the $|0\rangle$ state is also universal for quantum computation. In particular, *no coherent unitary dynamics are involved in the computation.*

Recall that in the standard quantum circuits model (see, for example, [1,2] for a review) a quantum computation consists of three elements: (a) an *initialization stage* in which the computer is prepared in an n -qubit computational basis state; (b) a *processing stage* in which a sequence of one- and two-qubit unitary gates is applied to the computer; and (c) a *read-out stage* in which the result of the computation is read out by measuring some subset of the qubits in the computational basis.

This paper demonstrates that a surprising alternate model is also universal for quantum computation. In this *measurement model* for quantum computation only the following three operations are allowed: (a) preparation of qubits in the $|0\rangle$ state; (b) storage of qubits (quantum memory); and (c) (non-destructive) projective measurements on up to four qubits at a time, in an arbitrary basis. What is surprising about the universality of this model is that no coherent dynamical operations are allowed, contrary to the widespread folklore belief that such operations are crucial to universal quantum computation.

Substantial prior work has been done on the physical requirements for universal quantum computation. Barenco *et al* [3] showed that controlled-NOT and single-qubit unitary operations are sufficient to do universal quantum computation. Deutsch, Ekert and Barenco [4] and Lloyd [5] showed that *almost any* two-qubit quantum gate is universal. More recently, Dodd *et al* [6] have shown that *any* two-body Hamiltonian entangling qubits, together with local unitary operations, is universal for computation. (See also related work in [7–10].)

Thus, the conventional approach to universality has been to identify a set of coherent dynamical operations universal for quantum computation. Recently, however, it has been realized that *quantum measurement* is a pow-

erful primitive element that can be performed during a computation. For example, Raussendorf and Briegel [11] have shown that by combining quantum measurements with the ability to prepare a special “cluster” state using a coherent Ising-type interaction, it is possible to do universal quantum computation. Knill, Laflamme and Milburn [12] have shown that single-photon detection and single-photon sources enable universal quantum computation in optics, using otherwise relatively easy coherent dynamical operations from linear optics.

In this paper I extend these results to show that no coherent dynamics at all are required to do universal quantum computation. The results of this paper build on a method developed by Nielsen and Chuang [13], who showed how to stochastically “teleport” a quantum gate from one location to another. Elegant generalizations of this method have been developed in [14–17]. The method has also been applied by Gottesman and Chuang [18] to develop fault-tolerant constructions for quantum gates, and further work [19] has been done simplifying such constructions. Note also that the optical quantum computer proposed by Knill, Laflamme and Milburn [12] is based on the gate teleportation idea.

In order to show that the measurement model can simulate the standard model of quantum computation we need only show that the measurement model can simulate the controlled-NOT gate, as well as any single-qubit unitary gate. We begin by explaining how the measurement model can simulate the action of an arbitrary single-qubit gate U on a single-qubit state $|\psi\rangle$.

The first step is to use the measurement model to prepare one of the two-qubit states $|U_j\rangle$ defined by $|U_j\rangle \equiv (I \otimes U\sigma_j)(|00\rangle + |11\rangle)/\sqrt{2}$, where σ_j are the four Pauli σ matrices, I, σ_x, σ_y , and σ_z . Simple algebra shows that these states form an orthonormal basis for the state space of two qubits, so we can achieve this state preparation by first preparing the state $|00\rangle$, and then measuring in the orthonormal basis of states $|U_j\rangle$. It is important to note that the construction presented below works no matter which of the four states $|U_j\rangle$ is output from this measurement procedure.

Having prepared the state $|U_j\rangle$ offline, we now attempt to use this state and Bell-basis measurements to perform the operation U on $|\psi\rangle$. The basic operation required to achieve this is the *gate teleportation* circuit shown in

*nielsen@physics.uq.edu.au

Fig. 1. Following [13], to analyse the output from the third line of this circuit, it is convenient to note that $U\sigma_j$ acting on the third qubit commutes with the Bell measurement on the first two qubits, so Fig. 1 is equivalent to Fig. 2. The circuit in Fig. 2 is easy to understand; except for the final gate $U\sigma_j$ acting on the third line, it is just quantum teleportation [20], and thus the final state output from the third line is $U\sigma_j\sigma_m|\psi\rangle$, where σ_m is one of the four Pauli matrices determined by the measurement result m from the Bell measurement. Note that each of the four possible outcomes $U\sigma_j|\psi\rangle, U\sigma_j\sigma_x|\psi\rangle, U\sigma_j\sigma_y|\psi\rangle$ and $U\sigma_j\sigma_z|\psi\rangle$ occurs with equal probability $1/4$.




FIG. 1. Circuit to teleport the gate U in the measurement model of quantum computation. The state $|U_j\rangle$ is prepared offline. $m = 0, 1, 2, 3$ is the outcome of the measurement in the Bell basis.




FIG. 2. This circuit produces the same output as Fig. 1, and is introduced merely to ease the analysis of Fig. 1. Note that not all the elements depicted in this circuit are allowed in the measurement model of quantum computation, while those in Fig. 1 are.

Thus, with probability $1/4$ the result m is the same as j , and the gate teleportation succeeds, with the gate U being applied to the qubit. With probability $3/4$, however, $m \neq j$, and the incorrect operation $U\sigma_j\sigma_m$ is applied to the qubit. At first glance this appears to create a significant problem, since we can't just discard the qubit and start again, as it may have been in an unknown state produced as part of a quantum computation. Fortunately, this problem can be avoided by teleporting the gate $U\sigma_m\sigma_jU^\dagger$. If this succeeds, which occurs with probability $1/4$, then the net action is $U\sigma_m\sigma_jU^\dagger U\sigma_j\sigma_m = U$, as desired. If the second gate teleportation fails, then the

net action is $U\sigma_m\sigma_jU^\dagger\sigma_{m'}\sigma_{j'}U\sigma_j\sigma_m$, where $|U_{j'}\rangle$ is the state that was prepared to do the second gate teleportation, and m' is the measurement result from the second gate teleportation. This is still okay, as we can use a similar gate teleportation procedure again to attempt to obtain the correct dynamics U . In general, the procedure we use to simulate U in the measurement model is as follows:

```

1  Initialization
2   $r := 1$  ; loop counter
3   $C_0 := I$  ; cumulative effect after 0 iterations
4  Main Loop
5   $A^r := UC_{r-1}^\dagger$  ; the gate we attempt to teleport
6  Prepare  $|A_{j_r}^r\rangle$ 
7  Teleport  $A^r$ , return result  $m_r$ 
8   $C_r := A^r\sigma_{j_r}\sigma_{m_r}C_{r-1}$  ; cumulative effect
9  Case:  $m_r = j_r$  ; success
10 Halt ; stop
11 Case:  $m_r \neq j_r$  ; failure
12  $r := r + 1$  ; update loop counter
13 Goto Main Loop ; try again

```

This procedure for simulating U has an intrinsic error probability due to the possibility of failure in the gate teleportation procedure. If we demand that the procedure succeed with probability one, then the procedure may be repeated an arbitrarily large number of times, making our simulation inefficient. Fortunately, an efficient construction can be devised, based on the threshold theorem for quantum computation [21–26]. The idea is to use the measurement model to simulate a fault-tolerant circuit in the standard model. In such a fault-tolerant circuit any element in the circuit can fail with some small probability $\epsilon > 0$ (currently estimates put ϵ in the range 10^{-4} to 10^{-6}), yet the circuit as a whole still succeeds with probability arbitrarily close to one. The single-qubit gates in the fault-tolerant circuit can thus be simulated in the measurement model, using at most r iterations of the gate teleportation procedure, where $(3/4)^r < \epsilon$. Thus the total number of operations required to simulate U in the measurement model scales as $O(\log(1/\epsilon))$. If we assume a threshold of 10^{-5} then we require $r = 41$ iterations to achieve a failure probability less than 10^{-5} .

Simulating two-qubit gates in the measurement model of quantum computation is similar to simulation of single-qubit gates. Let U now denote an arbitrary two-qubit quantum gate. To simulate U we first define $|U_{jk}\rangle$ to be the result of applying $U(\sigma_j \otimes \sigma_k)$ to the third and fourth qubits of $(|00\rangle_{13} + |11\rangle_{13}) \otimes (|00\rangle_{24} + |11\rangle_{24})/2$, where the subscripts label which qubit is being referred to. Such a state can be prepared by first preparing the state $|0000\rangle$ and then measuring in the orthonormal basis $|U_{jk}\rangle$. Gate teleportation is now achieved using Fig. 3, in a fashion analogous to the single-qubit case. Once again, the number of operations necessary to achieve a failure probability at most $\epsilon > 0$ is $O(\log(1/\epsilon))$ operations in the measurement model.




FIG. 3. Circuit to teleport the two-qubit gate U in the measurement model of quantum computation. The state $|U_{jk}\rangle$ is prepared offline. Two Bell-basis measurements are done, one on the first and third qubits, with outcome $m = 0, 1, 2, 3$, and the second on the second and fourth qubits, with outcome $n = 0, 1, 2, 3$. It will be useful below to refer to this joint basis of the four qubits as the “Bell basis for four qubits”. The output of the circuit is $U_{jk}(\sigma_m \otimes \sigma_n)|\psi\rangle$, by a similar analysis to the single-qubit case.

We have shown that universal quantum computation can be performed using measurements, quantum memory, and preparation of the $|0\rangle$ state. This result appears rather mysterious — after all, isn’t it the ability to evolve coherently that is most important to quantum computation? Some insight may be gained by noting that a similar model is universal for classical computation. Suppose we have the following three abilities: (a) preparation of arbitrary probability distributions over four bits; (b) storage of bits (memory); and (c) measurements on up to four bits at a time. To see that this model of computation is universal for classical computation, suppose for example that we want to simulate the NOT gate on a single bit; it will be clear how to generalize the result to arbitrary one- and two-bit gates. To do the simulation, first prepare two bits in the state $(Y, \text{NOT}(Y))$, where Y is a classical random variable which is zero with probability $1/2$ and one with probability $1/2$. To apply the NOT gate to a classical bit x we perform a measurement of the first two bits of the string $(x, Y, \text{NOT}(Y))$. This measurement has two outcomes, which correspond to the case when x is the same as Y , in which case the third bit finishes in the state $\text{NOT}(x)$, and the protocol succeeds, and the case when x is different to Y , in which case the protocol fails, with the output of the third bit being x . Fortunately, it is possible to repeat the protocol so that with just a few repetitions we obtain a high probability of successfully applying a NOT gate. It is straightforward to generalize this construction to any classical gate, and thus to perform universal classical computation using the preparation of arbitrary probability distributions over four bits, memory, and measurements on up to four bits at a time.

What effect does experimental noise have on the measurement model of quantum computation? It is straightforward to prove that an analogue of the threshold theorem for the standard model of quantum computation [21–26] holds in the measurement model. In brief, the idea is that for any circuit in the measurement model,

we can construct an equivalent circuit in the standard model of quantum computation, then make that circuit fault-tolerant using well-known procedures, and finally obtain a fault-tolerant circuit in the measurement model by simulating the fault-tolerant circuit in the standard model. This procedure for obtaining fault-tolerant circuits in the measurement model is rather indirect, and it would be interesting to obtain a fault-tolerant construction more directly, and to compare the threshold thus obtained to thresholds in the standard model of quantum computation.

Does the measurement model of quantum computation have any practical implications as a means of simplifying experimental proposals for quantum computation? Unfortunately, the four-qubit projective measurements used in the present construction are not easily implemented in most physical systems, and thus the construction is mainly of theoretical interest. However, it may be possible to simplify the measurements sufficiently that the model is of practical interest, ideally by reducing the number of systems involved in the measurements being performed.

We have shown that universal quantum computation can be performed using projective measurement, quantum memory, and the ability to prepare the state $|0\rangle$. This result emphasizes the power that comes from the ability to perform measurements during a computation. The simplicity of the model may also make it useful for the study of quantum computational complexity. Finally, by showing that coherent dynamical operations are not necessary for universal quantum computation, the model gives valuable insight into the fundamental question of what gives quantum computers their power.

ACKNOWLEDGMENTS

This paper was stimulated by a discussion with Damian Pope about what makes quantum computers powerful. Thanks to Michael Bremner, Ike Chuang, Jennifer Dodd, Alexei Gilchrist, Tobias Osborne, and Damian Pope for a thorough reading of the manuscript.

-
- [1] M. A. Nielsen and I. L. Chuang, *Quantum computation and quantum information* (Cambridge University Press, Cambridge, 2000).
 - [2] J. Preskill, *Physics 229: Advanced mathematical methods of physics — Quantum computation and information* (California Institute of Technology, Pasadena, CA, 1998), <http://www.theory.caltech.edu/people/preskill/ph229/>.
 - [3] A. Barenco *et al.*, Phys. Rev. A **52**, 3457 (1995), quant-ph/9503016.

- [4] D. Deutsch, A. Barenco, and A. Ekert, Proc. Roy. Soc. London A **449**, 669 (1995).
- [5] S. Lloyd, Phys. Rev. Lett. **75**, 346 (1995).
- [6] J. L. Dodd, M. A. Nielsen, M. J. Bremner, and R. Thew, arXiv eprint quant-ph/0106064 (2001).
- [7] P. Wocjan, D. Janzing, and T. Beth, arXiv eprint quant-ph/0106077 (2001).
- [8] D. Janzing, P. Wocjan, and T. Beth, arXiv eprint quant-ph/0106085 (2001).
- [9] C. H. Bennett *et al.*, arXiv eprint quant-ph/0107035 (2001).
- [10] D. W. Leung, arXiv eprint quant-ph/0107041 (2001).
- [11] R. Raussendorf and H. J. Briegel, Phys. Rev. Lett. **86**, 5188 (2001).
- [12] E. Knill, R. Laflamme, and G. J. Milburn, Nature **409**, 46 (2001).
- [13] M. A. Nielsen and I. L. Chuang, Phys. Rev. Lett. **79**, 321 (1997).
- [14] G. Vidal and J. I. Cirac, arXiv eprint/quant-ph/0012067 (2000).
- [15] G. Vidal, L. Masanes, and J. I. Cirac, arXiv eprint quant-ph/0102037 (2001).
- [16] S. F. Huelga, J. A. Vaccaro, A. Chefles, and M. B. Plenio, arXiv eprint quant-ph/0005061 (2000).
- [17] S. F. Huelga, M. B. Plenio, and J. A. Vaccaro, arXiv eprint quant-ph/0107110 (2001).
- [18] D. Gottesman and I. L. Chuang, Nature **402**, 390 (1999), arXiv eprint quant-ph/9908010.
- [19] X. Zhou, D. W. Leung, and I. L. Chuang, Phys. Rev. A **62**, 052316 (2000).
- [20] C. H. Bennett *et al.*, Phys. Rev. Lett. **70**, 1895 (1993).
- [21] M. A. Nielsen, Phys. Rev. A **63**, 022114 (2001), arXiv eprint quant-ph/0008073.
- [22] D. Aharonov and M. Ben-Or, arXiv eprint quant-ph/9906129 (1999).
- [23] D. Gottesman, Ph.D. thesis, California Institute of Technology, Pasadena, CA, 1997.
- [24] A. Y. Kitaev, in *Quantum Communication, Computing, and Measurement*, edited by A. S. H. O. Hirota and C. M. Caves (Plenum Press, New York, 1997), pp. 181–188.
- [25] E. Knill, R. Laflamme, and W. H. Zurek, Proc. Roy. Soc. A **454**, 365 (1998), arXiv eprint quant-ph/9702058.
- [26] J. Preskill, Proc. Roy. Soc. A: Math., Phys. and Eng. **454**, 385 (1998).